



The MX51s is a four channel mixer designed for Audio and Visual applications. Channel 1 has a microphone XLR input with selectable phantom power. Channel 2 has both 1/8" and RCA inputs. Channels 3 and 4 have RCA inputs. The MX51s also features a 1/8" line or headphone output that will drive up to 600 Ω headphones. It has enough output level to connect to any power amplifier. The MX51s is powered by an included ROLLS PS27s adapter.

# ROLLS

## MX51s 4-Channel Mixer

- Studio
- Live
- Broadcast

Anywhere you need to mix up to four signals to a single output.

What's in the box?

- 1 - Made in USA MX51s
- 1 - 15V power supply PN PS27s
- 1 - This owners manual

### SPECIFICATIONS

Input Impedance:	10K Ω unbalanced each jack
CH 1 Gain:	32 dB XLR jack (highest gain)
Phantom Power:	for CH 1 microphone XLR
CH 2 Gain:	26 dB 1/8" and RCA
CH 3 and 4 Gain:	26 dB each RCA
Output:	1/8" stereo and stereo RCA
S/N Ratio:	>90 dB
THD:	<.008%
IMD(SMPTE):	<.008%
Power:	ROLLS PS27s 15 VDC adapter
Weight:	1 lbs. (.45 Kg)
Size:	3" x 5" x 1.25" (8 x 13 x 3.2 cm)